



Bluetooth Visor Clip with Caller ID





Fully charge unit before use.

1. Turning on the unit

Press and hold the power button to turn on the Bluetooth Visor Clip, it will automatically pair to the external BT device, if previously paired. To shut off unit, press and hold power button.

2. Pairing Mode

To pair for the first time open Bluetooth settings on your phone. Search for other devices. Power on the speaker by pushing .

Then hold down the  on the speaker. Display will show "pairing", then flashes "-bt". LED will blink red and blue. Select pairing name "AA Speaker ID" from your phone. The Bluetooth Visor Clip will then say "connected" when complete.

3. Viewing Screen Displays

After turning on the Bluetooth Visor Clip, the screen may show "PAIRING" until it enters pairing mode. Once you have activated the device, the screen will be show "-bt-".

When there is an incoming call, you will see the calling number on the viewing screen. When a call is in progress, "CALLING" shows up. Ending the call "HANGUP" shows up. Turning off the speaker, "OFF" shows up.

4. Function of LED indicator

RED LED is on when the battery is charging.

RED LED is off when the battery is fully charged.

RED and BLUE LED blink alternately when the Bluetooth Visor Clip is in pairing mode.

RED LED blinks with sound alert when the battery has low power.

5. Button Functions



volume increase



volume decrease



Play / Pause / Answer Call



On / Off / Pairing / End Call

Specification

Bluetooth version	Bluetooth V3.0 + EDR
Transmission Power	Class 2
Operating Range	10 Meter
Frequency Range	2402 MHz~2480GHz ISM Ban
Microphone Specification	-42db (0dB=1V/Pa,1KHz)
Talking Time	5 hours
Standby Time	120 hours
Charging Voltage	5V
Charging Current	200MA
Charging Time	2-3 hours
Accessories	Micro USB Cable, User's Manual, Visor Clip
Battery	5C Lithium Battery, 500 mAH
Speaker	2W/8Ω*1 Ø40mm
Color	Black
Weight	83.6g
Size	110.2*19.3*43.3mm

Toll Free: 877-405-2397

info@armorallelectronics.com

www.armorallelectronics.com